

WATTAGE - 20 watts to 100 watts available.

INPUT VOLTAGE - 120VAC to 277VAC available.

OUTPUT VOLTAGE - 12VDC and 24VDC available.

PROTECTION - Short circuit / Over current / Over voltage

WARRANTY - 2 years from date of purchase.

LISTINGS - U.L. recognized.

Constant voltage LED drivers.



Output VDC	Watts	Input VAC	Electronic Non-Dimming	Electronic 0-10 Dimming	Dimensions LxWxH	DRIVER
12	20	110-230	✓		4.6" x 1.4" x 1"	DSH-DR20-12V
12	35	110-230	✓		5.8" x 1.5" x 1"	DSH-DR35-12V
12	60	110-230	✓		6.4" x 1.7" x 1.25"	DSH-DR60-12V
12	60	110-277		✓	9.5" x 1.75" x 1.2"	DSH-DR60-12V-DIM
12	100	100-240	✓		7.5" x 2.2" x 1.5"	DSH-DR100-12V
24	20	110-230	✓		4.6" x 1.4" x 1"	DSH-DR20-24V
24	35	110-230	✓		5.8" x 1.5" x 1"	DSH-DR35-24V
24	60	110-230	✓		6.4" x 1.7" x 1.25"	DSH-DR60-24V
24	96	110-277	✓		9.5" x 1.75" x 1.2"	DSH-DR96-24V
24	96	110-277		✓	9.5" x 1.75" x 1.2"	DSH-DR96-24V-DIM